

## DJS-B-1 2.5 Digits 1 Color LED Countdown Timer

### Design For:

With a patent design of 7 segments LED Countdown Timer, This device was designed for count how many seconds for the LED Traffic Lights left, which can remind the drive how many seconds more they need to wait, help to reduce the traffic accidents;

### Special Features:


1. **Unique Design:** Tool free, open and maintain the traffic light without any special tool
2. **High Brightness:** with the best quality LED components
3. **Long Life:** up to 50,000 hours, adopts PWM constant current power, protects LED efficiently
4. **Energy Saving:** With a very low power consumption which can save up to 80-90% energy
5. **IP Rating:** IP65, sealed moisture resistant enclosure
6. **Related approvals:** CE, Chinese GB14887-2003 standards, and related international standards

### Specifications:

Luminous Components	Emission Color	Display Mode	Character Height	LED Quantity	Luminous( cd)	Wavelength(nm)
LED	Red	0-199	20 inch	496	$\geq 4000/m^2$	$625 \pm 5$
Housing Material	Armor Plate					

Visual Distance (m)	Power Consumption (w)	Operating Temperature (°C)	Working Voltage	Dimension (mm)
$\geq 200$	$\leq 40W$	-40~+80	80V~280AC 50/60Hz	820x600x80

### Packing Info.

	Unit Packing:	1 Set/Carton Box
	Dimension (mm):	850x625x170
	N.W./G.W.(kg):	17.0 / 18.5
	Volume(m <sup>3</sup> ):	0.08
	20'Q Q'ty (pcs):	273
	40'Q Q'ty (pcs):	585

Contact: **Jason Yang** ([jasonyang@bbeled.com](mailto:jasonyang@bbeled.com)), Marketing and Sales Manager, Sales Department  
**Shenzhen Bang-Bell Electronics Co., Ltd.**, / Website: [www.bbeled.com](http://www.bbeled.com)

Tel.: 0086 755 2958 8988 Fax: 0086 755 2958 8616 Mobile: 0086 138 2317 7749